

Architectural & Engineering Specifications

SPA 2240 –Amplifier

SPA 2240 Amplifier

The unit shall be an Ateis UK SPA2240 or equal and approved.

The unit shall comprise a steel rackmountable case with all connections and controls on the rear panel to deter unauthorised adjustments.

The unit shall include two totally independent amplifier channels with independent inputs, outputs and AC/DC power supplies such that a failure of one amplifier channel does not affect the operation of the second channel.

The unit shall be powered from both AC and DC power if required for voice alarm applications, and shall include power supply and amplifier overload surveillance with front panel indication and rear panel fault output contacts.

Amplifier input sensitivity shall be set via a rear panel rotary gain control with an associated control defeat switch.

Signal level shall be indicated via a front panel LED Array.

The unit shall provide the following:

- 2U 19" Case
 - 483W x 88H x 420D mm
 - Forced air cooling
 - Temperature controlled
 - 18.5kg Nett weight
- AC Power Supply
 - 230V +/-10%
 - 50Hz - 60Hz
 - Supply surveillance

Dual power supply

1 transformer/psu per channel

Rear panel power switch

IEC connector

- AC Power Consumption Per Channel 230V

0.28A Quiescent

1.25A Typical speech message

1.65A Typical alarm tone & message

2.2A Typical alarm tone

2.85A Nominal power

- DC Power Supply

21V - 28V

Supply surveillance

Dual power supply

1 DC inlet/PSU per channel

Screw terminal Euro-Block plug

- DC Power Consumption Per Channel 28V

0.3A Quiescent

5.47A Typical speech message

7.5A Typical alarm tone & message

10.4A Typical alarm tone

12.3A Nominal power

- Control And Indication (Per Channel)

LED Signal level bargraph

Front panel

LED Power present

Front panel

LED Power fault

Front panel

LED Amplifier overload fault

Front panel

LED Amplifier temperature fault

Front panel

Rotary gain control

Rear panel

Switch activation

Architectural & Engineering Specifications

SPA 2240 –Amplifier

- Fault relay output
Rear panel
- Audio Inputs (Per Channel)
 - Balanced line level input
 - 770mV rms Sensitivity
 - 20k Ohm impedance
 - Female XLR
 - Screw terminal Euro-Block plug
 - Slave Audio Outputs (Per Channel)
 - Balanced line level output
 - Male XLR
 - Screw terminal Euro-Block plug
 - Main Audio Outputs (Per Channel)
 - 70V & 100V Line high impedance
 - 4 Ohm - 8 Ohm Low impedance
 - Screw terminal Euro-Block plug
 - Audio Performance
 - 2 x 240W Nominal output
 - Bridgeable output stages
 - <1% THD at nominal power
 - >90dB S/N ratio
 - 60Hz - 18kHz Frequency response

IMPORTANT

Specifications are subject to change without prior notice. More information can be found at the website: www.ateis.co.uk.

© 2009 Ateis UK Ltd



Ateis UK Ltd
102 Victoria Street
St. Albans
Hertfordshire
AL1 3TG

T: 08456 521 511
F: 08456 522 527
E: infoplease@ateis.co.uk
Web: www.ateis.co.uk